

Bellows Chamber Kits

406854B

ENG

Merkur[™] Bellows Pumps



Important Safety Instructions

Read all warnings and instructions in manuals 312793 and 312795. Save all instructions.

See reverse for parts illustration and assembly notes.

TIP: Some o-rings are close in size. Stack on bench to differentiate.


Kit 24E758, LB050x (50cc) pumps Kit 24E759, LB100x (100 cc) pumps Kit 24E760, LB150x (150cc) pumps

		Size in. (mm)			
Ref	Description	24E878	24E759	24E760	Qty
101	O-RING, packing nut top	1.9 (48)	1.9 (48)	1.9 (48)	1
102	O-RING, bellows chamber	2.5 (64)	2.5 (64)	2.5 (64)	1
103	WASHER				1
104	SCREW, M6 x 25				1
105	CHAMBER, bellows				1
106	O-RING, foot cap	1.8 (46)	2.4 (61)	2.7 (69)	1
107	FITTING, inlet	3/4 in. npt	3/4 in. npt	1 in. npt	1
108	O-RING, inlet fitting	1.0 (25)	1.0 (25)	1.0 (25)	1
109*	O-RING, packing nut bottom	1.6 (41)	2.0 (51)	2.3 (58)	1
110**	O-RING, piston	0.6 (15)	0.8 (20)	0.8 (20)	1

^{*} May not be used. Remove packing nut only if necessary. If removed, replace o-rings before reassembly.

^{**} May not be used. Piston and rod may separate during disassembly. If separated, always replace the o-ring before reassembly.

NOTE: Full disassembly shown. Disassemble only as far as needed for the parts being replaced.



Apply grease.

Apply thread lubricant.

③ Torque to 100-120 in-lb (11-14 N•m).

△ Torque to 54-66 ft-lb (73-89 N•m).

5 Torque to 74-86 ft-lb (100-117 N•m).

6 Torque to 91-109 ft-lb (123-148 N•m).

Apply high-strength thread locker.

2 406854B